

## ***Features***

- Fully compliant with PCI Express Base Specification Revision 2.0
- Single-lane (x1) PCI Express throughput rates up to 5 Gbps
- Compliant with Universal Serial Bus 3.0 specification Revision 1.0
- Supports simultaneous operation of multiple USB 3.0, USB 2.0 and USB 1.1 devices
- Supports the following speed data rates as follows:
- Low-speed (1.5Mbps)/Full-speed (12Mbps)/High-speed(480Mbps) / Super-speed (5Gbps)
- Full speed on each port
- Built-in 4 phase power module 1 for each port. No extra power required from system
- Hot-swapping feature allows you to connect/disconnect devices without powering down the system
- Support Windows® XP/Vista/7/8/8.1/10 (32/64 bit)

## ***System Requirements***

- Windows® XP/Vista/7/8/8.1/10 (32/64 bit)
- One available PCI Express slot (Recommend PCI Express 2.0)

## ***Package Contents***

- 1 x EkoBuy® 4 Port USB 3.0 PCI Express Card
- 1 x Software Drivers CD

Note: Contents may vary depending on country/market.

## ***Hardware Installation***

1. Turn Off to your computer fully.
2. Unplug the power cord wait about 5 minutes and remove your computer's cover.
3. Remove the slot bracket from an available PCIe slot.
4. To install the card, carefully align the card's bus connector with the selected PCIe slot

on the motherboard. Push the board down firmly.

5. Replace the slot bracket's holding screw to secure the card.
6. Replace the computer cover and reconnect the power cord.

### **Driver Installation**

#### **<For Windows® 8/8.1/10 (32/64 bit)>**

*You don't need to install driver for Windows® 8 / 8.1 /10 Windows® already has built in drivers*

#### **<For Windows® XP/Vista/7 (32/64 bit)>**

1. Please insert the CD driver bound with USB 3.0 PCI Express Card into your CD-ROM Drive.
2. At the Windows desktop, click **Start, Run**.
3. Type **X: \Setup.exe**, click **OK**. (Change X: to match your CD-ROM drive letter)
4. Follow the on-screen instructions to complete the installation.

### **To Verify Driver Installation**

Click on the "**Device Manager**" tab in System Properties, which you access from the Windows Control Panel. You should see a "**Renesas Electronics USB 3.0 Host Controller**" under the "**Universal Serial Bus controllers**" item.

### **Notice:**

The extended compatibility works better if insert the card in the first slot or the 16X slot.